

Samsung SPE-100/400 Causes Server Crash

Symptom:

exacqVision Server crashes when connecting to a Samsung SPE-100/400 using the native Samsung plugin.

Problem:

This encoder is only supported for use with the Onvif plugin (device type).

Additionally, the device firmware only supports HTTP version 1.0 but Live555 defaults to 1.1.

Solution:

Connect to the device with the Onvif device type on the 'Add IP Cameras' page.

Add the '#http=1.0' override option to the 'Hostname/IP Address' field.

If the device IP is 192.168.0.5, change it to read 192.168.0.5#http=1.0